



EGO 210w Power+ 56 Volt Charger

REGCH2100



Details

The EGO POWER+ 56 Volt Charger boasts industry leading recharge times. In just 40 minutes, a depleted 2.0 Ah battery can be fully recharged with the 56-Volt Charger. The active cooling fan system supports rapid charging without overheating. The quick recharge capability ensures limited downtime with any battery in the EGO platform. Please note: This product is restricted from air freight, and will only be shipped ground freight

- Industry's Leading Recharge Time
- Integrated Fuel Gauge Shows How Much Power is Left in the Battery
- Integrated LED Charge Indicator Lights Shows Charge Amount
- Fan Cooled Preventing Battery and Charger From Overheating
- Charges All EGO POWER+ Batteries
- Approximate Charge Time from Zero to Full Charge as Follows:
 - 2.0 Ah Battery 40 Minutes
 - 2.5 Ah Battery 50 Minutes
 - 4.0 Ah Battery 80 Minutes
 - 5.0 Ah Battery 100 Minutes
 - 7.5 Ah Battery 145 Minutes
- Complies with CEC Requirements

Specifications

Manufacturer EGO

GA Power Equipment Spares

11 Sodium St Narangba, 4504
1300 363 004

<https://rgs.rproducts.com/>